

EST-808BJ

Portable high power remote control bomb jammer Radio-Controlled Improvised Explosive Device(RCIED) jammer

Features

- Shielding Radius: 200-300m
- Type: Portable Bomb Jammer / RCIED Jammer
- Frequency Band(can be customized):
 - 1st Channel: 20-50MHz----- Remote Control (RC) toys / HF radio
 - 2nd Channel: 50-100MHz----- FM radio
 - 3rd Channel: 135-175MHz----- VHF radio
 - 4th Channel: 300-340MHz----- RC315
 - 5th Channel: 400-470MHz----- RC433 / UHF radio
- Function: counter-RCIED, effectively block 20-470MHz low frequency radio remote control signals within 300 meters, then the bomb can't be detonated by remote control
- Portable trolley case design, convenient to carry and use, built-in battery, high-power cooling fans, real-time voltage display, low battery alarm, military quality
- Single Output Power(each band): 48dBm/70W
- Battery Type: built-in 24V 60AH lithium battery(can continuously work for 1-2 hours on a full charge)
- Power Supply(Charger): AC / DC adapter(Input: AC100-240V; Output: DC27V 80A) / DC29.4V/5A external emergency power external emergency power
- Dimension: 510*360*610 mm not include antenna(with antenna height in 1.5m)
- Host Weight: 50kg

Applicable Place

- Battlefield, SWAT, border guard, army, counter-terrorism unit, detention center, president election, speech, big event, olympic games, etc.
- At other places where there is a remote control bomb(RCIED) threat

